MECHANICAL FREQUENCY CONVERTERS - NW

> SCAN QR CODE FOR MAINTENANCE & INSTALLATION DOCUMENTS

- Converters for 42V-200 Hz vibrators allowing continuous operation and up to 4 sockets connected simultaneously on the 5 kVA model.
- Permanent magnet generator to ensure operator safety in the presence of low voltage equipment.
- Protection by tubular cage or trolley on wheels facilitating handling.

We reserve the right to change specifications and dimensions without notice.

TECHNICAL SPECIFICATIONS							
Model	**Connection**	**Maximal Power**	**Voltage nominal**	**Maximal Power**	**Capacity**	**Mobilty**	**Weight**
	-	kVA	V - Hz	A	-	-	KG
NW0582	TREE-PHASE	1	**42 - 200**	**14**	1 Ø 38/50	X	**17**
NW0588	SINGLE-PHASE	1	**42 - 200**	**14**	1 Ø 38/50	X	**17**
NW0586	TREE-PHASE	2	**42 - 200**	**28**	2 Ø 38/50 1 Ø 38/50 + 1 Ø 60 1 Ø 60/70	Sledge	**25**
NW0590	SINGLE-PHASE	2	**42 - 200**	**21**	2 Ø 38/50 1 Ø 38/50 + 1 Ø 60 1 Ø 60/70	Sledge	**25**
NW0600	TREE-PHASE	3	**42 - 200**	**42**	3 Ø 38/50 2 Ø 38/50 + 1 Ø 60/70 2 Ø 60/70 1 Ø 80/90	Sledge	**33**
NW0620	SINGLE-PHASE	3	**42 - 200**	**35**	3 Ø 38/50 2 Ø 38/50 + 1 Ø 60/70 2 Ø 60/70 1 Ø 80/90	Sledge	**33**
NW0500	TREE-PHASE	3	**42 - 200**	**70**	4 Ø 38/50 4 Ø 60/70 4 Ø 80/90	On Wheel	**80**

The technical information, diagrams and images present in this document are the exclusive property of Vibraxtion Sarl. Any reproduction is prohibited. This information is non-contractual.